

Accessory

Compensator

Type: 6596

GTIN: 4011395638507

Prevents the self-ignition of energy-saving or LED lamps during switching with orientation illumination (parallel to the lamp). Prevents after-glow of low-voltage halogen or LED lamps in a deactivated state due to possible ripple voltage or activation via touch-dimmer without neutral conductor connection (parallel to the primary transformer side or to the lamp). Removes noise generation on electronic transformers in a switched-off state during activation via touch-dimmer without neutral conductor connection (parallel to the primary transformer side). Removes ripple voltages on the control line in blind control/group controls (parallel between control wire "UP" and neutral conductor as well as "Down" and neutral conductor). Dimensions: diameter 22 mm, length 25 mm, length of the connecting cable approx. 235 mm. Rated voltage: 250 V~ Rated frequency: 50 Hz



Technical specification

General Information

Product ID:	2CKA006599A2290
-------------	-----------------

Packing

Package:	1/10
Unit:	PCS

ETIM Data

Accessory:	No
Spare part:	No