

Button / Buzzer

Button / Buzzer, 1-fold



Typ: FIP1011

Produkt ID: 2TKA00003793

GTIN: 6438199005225



A device including a push button as well as a buzzer. The LED of the push button and the buzzer operates in parallel. The buzzer can be cancelled with the push button. When cancelled the LED remains on till the alarm goes off. Good marking possibilities on the push button and the name plate. Operating voltage 9,5 - 28 Vac / 9,5 - 35 Vdc. Current consumption: 45 mA ac / 25 mA dc. Load capacity of the switch: 30 Vac / 35 Vdc, 100 mA ac/dc, 3 VA / 3 W.

Teknisk specifikation

Elektriska värden

| | |
|----------------------|-------------------------------|
| Operating voltage: | 9,5 - 28 V ac / 9,5 - 35 V dc |
| Current consumption: | 45 mA ac / 25 mA dc |

Signal products

| | |
|-----------------------------------|---------------------------------|
| Sound frequency: | 400 Hz, 70 dB / 30 cm |
| Loading capacity of switch (max): | 100 mA ac/dc, 30 V ac / 35 V dc |

Packning

| | |
|--------------|---------------|
| Förpackning: | 1/10/100/1200 |
| Enhet: | st |

ETIM Data

| | |
|----------------------------|----------|
| ETIM Version: | ETIM-9.0 |
| ETIM Class: | EC002247 |
| Colour: | White |
| RAL-number (similar): | 9010 |
| Degree of protection (IP): | IP20 |
| Device width: | 71 mm |
| Device height: | 39 mm |
| Device depth: | 71 mm |