

Button / Buzzer

Button / Buzzer, 1-fold

**Tyyppi:** FIP1011**Tuotekoodi:** 2TKA00003793**GTIN:** 6438199005225

A device including a push button as well as a buzzer. The LED of the push button and the buzzer operates in parallel. The buzzer can be cancelled with the push button. When cancelled the LED remains on till the alarm goes off. Good marking possibilities on the push button and the name plate. Operating voltage 9,5 - 28 Vac / 9,5 - 35 Vdc. Current consumption: 45 mA ac / 25 mA dc. Load capacity of the switch: 30 Vac / 35 Vdc, 100 mA ac/dc, 3 VA / 3 W.

Tekniset tiedot

Sähkösuureet

Operating voltage:	9,5 - 28 V ac / 9,5 - 35 V dc
Current consumption:	45 mA ac / 25 mA dc

Signal products

Sound frequency:	400 Hz, 70 dB / 30 cm
Loading capacity of switch (max):	100 mA ac/dc, 30 V ac / 35 V dc

Pakkaus

Paketti:	1/10/100/1200
Yksikkö:	kpl

ETIM Data

ETIM Version:	ETIM-9.0
ETIM Class:	EC002247
Colour:	White
RAL-number (similar):	9010
Degree of protection (IP):	IP20
Device width:	71 mm
Device height:	39 mm
Device depth:	71 mm