


Switch insert


Double pole 1-gang 2-way switch insert, 16AX/250V, no X-terminals, lamp possibility



Tyyppi: 10662.00

Tuotekoodi: 2TKA000177G1

GTIN: 6418677328657



2-pole change-over switch insert without rocker. All 1-gang rockers are suitable for the insert except 1788-xx. The switch has 2 change-over contacts, but no X-terminals. A signal- or searchlight can be installed to the frame.

Tekniset tiedot

Sähkösuureet

Nominal voltage:	250 V
Rated current:	16 AX

Luokitus

Suitable for degree of protection (IP):	IP21
---	------

Pakkaus

Paketti:	10/100
Yksikkö:	kpl

ETIM Data

Tuotekortti

Double pole 1-gang 2-way switch insert, 16AX/250V, no X-terminals, lamp possibility



ETIM Version:	ETIM-9.0
ETIM Class:	EC001590
Wiring system:	Other
Method of operation:	Rocker/button
Assembly arrangement:	Basic element with full cover plate
Push button switch:	Ei
Number of rockers:	2
Mounting method:	Flush mounted (plaster)
Type of fastening:	Screw mounting
With mounting plate:	Ei
Material:	Plastic
Material quality:	Thermoplastic
Halogen free:	Kyllä
Anti-bacterial treatment:	Ei
Surface protection:	Galvanized
Colour:	Stainless steel
RAL-number (similar):	9016
Label space/information surface:	No
Illumination:	No
Rated current:	16 A
Switching current for fluorescent lamps:	16 AX
Feedback-signal contact:	Ei
Connection type:	Other
Washing machine switch:	Ei
Device width:	70 mm
Device height:	40 mm
Device depth:	85 mm
Built-in depth:	18 mm
Min. depth of built-in installation box:	18 mm