

IR Remote Control

Type: 6843-101

Product ID: 2CKA006899A0001

GTIN: 4011395366264



For Busch-Presence detector BasicLINE.

With transmission LED.

With 3 keypads for different device settings/functions.

The following functions/settings can be implemented, dependend on device type.

Permanents light or OFF for 10 h.

Activate automatik mode.

Activate semiautomatic operation mode.

Setting of the brightness limit value.

Setting of the current ambient light value as the brightness limit value.

Setting of switch-off delay or short-time pulse.

Increasing / decreasing the sensitivity.

Adjusting the detection range (only for microwave detector).

Selection of channel 1 or channel 2 (only for devices with HVAC function).

Activate 2-step automatic switch-off function.

Increasing / decreasing the load brightness (only for DALI detector).

Setting of constant light brightness value (only for DALI detector).

Activate test mode.

Activation/deactivation of the button lock.

Reset to factory default settings (only for microwave detector).

IR transmission range: frontal 3 m.

Power supply: lithium button cell battery Type CR2032, included.