

Socket outlet

Busch-steplight Socket insert Safety Shutter Night orientation light with Night light; LED /White white - Busch-balance SI



Typ: 20 EUCBLI-916-510

Produkt ID: 2CKA002013A5487

GTIN: 4011395316245

Shuttered. With screwless terminals. DP (2 P + E) with separate connection cables for switch contact. with LED,

Teknisk specifikation

Elektriska värden

Nominal current:	16 A
Nominal voltage:	250 V

Klassificering

Suitable for degree of protection (IP):	IP20
---	------

Packning

Förpackning:	1/1
Enhet:	st

ETIM Data

ETIM Version:	ETIM-9.0
ETIM Class:	EC000125
Number of active pins (round):	2

Produktblad

Busch-steplight Socket insert Safety Shutter Night orientation light with Night light; LED /White white - Busch-balance SI



With signal lamp:	Nej
Number of units:	1
Number of phases:	1
Imprint/indication:	None
With hinged lid:	Nej
With enhanced contact protection:	Nej
Label space/information surface:	Nej
Colour:	Other
RAL-number (similar):	9003
Metallic colour:	Nej
Transparent:	Nej
Lockable:	Nej
Eject-mechanism:	Nej
Insulated mounting:	Ja
With function lighting:	Nej
With orientation lighting:	Nej
Over voltage protection:	Nej
Fault current protection:	Nej
With miniature fuse:	Nej
Special power supply:	Supplementary safety power supply (orange)
Mounting method:	Flush mounted (plaster)
Type of fastening:	Mounting with claw and screw
Material:	Plastic
Material quality:	Thermoplastic
Halogen free:	Nej
Surface protection:	Untreated
Surface finishing:	Glossy
Anti-bacterial treatment:	Nej
With loop through function:	Nej
With on/off switch:	Nej
Rotated central insert:	Nej
Impact strength:	IK03
Device width:	71 mm
Device height:	71 mm

Produktblad

Busch-steplight Socket insert Safety Shutter Night orientation light with Night light; LED /White white - Busch-balance SI



Device depth:	50 mm
Min. depth of built-in installation box:	32 mm
Compatible with Apple HomeKit:	Nej
Compatible with Amazon Alexa:	Nej
Compatible with Google Assistant:	Nej
IFTTT support available:	Nej
With Wi-Fi signal repeater:	Nej
With built-in bluetooth speaker:	Nej