


# Signal device

## Signal device White - Saga

**Typ:** FIP1011-916

**Produkt ID:** 2TKA00004977

**GTIN:** 6438199010977



A device including a push button as well as a buzzer. The LED of the push button and the buzzer operates in parallel. The buzzer can be cancelled with the push button. When cancelled the LED remains on till the alarm goes off. Good marking possibilities on the push button and the name plate. Operating voltage 9,5 - 28 VAC / 9,5 - 35 V DC. Current consumption: 45 mA AC / 25 mA DC. Load capacity of the switch: 30 VAC / 35 VDC, 100 mA AC/DC, 3 VA / 3 W.

## Teknisk specifikation

### Packning

Förpackning:	1/10/100/1200
Enhet:	st

### ETIM Data

ETIM Version:	ETIM-9.0
ETIM Class:	EC002247
Model:	Buzzer
Colour:	White
RAL-number (similar):	9003
Voltage type:	AC/DC
Nominal voltage AC:	9.5...28 V
Nominal voltage DC:	9.5...35 V

With transformer:	Nej
Degree of protection (IP):	IP20
Device width:	71 mm
Device height:	40 mm
Device depth:	71 mm